

	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
<i>0</i>	NOP	LXI B,	STAX B	INX B	INR B	DCR B	MVI B,	RLC	DSUB*	DAD B	LDAX B	DCX B	INR C	DCR C	MVI C,	RRC
<i>1</i>	ASRH*	LXI D,	STAX D	INX D	INR D	DCR D	MVI D,	RAL	RLDE*	DAD D	LDAX D	DCX D	INR E	DCR E	MVI E,	RAR
<i>2</i>	RIM	LXI H,	SHLD	INX H	INR H	DCR H	MVI H,	DAA	LDEH*	DAD H	LHLD	DCX H	INR L	DCR L	MVI L,	CMA
<i>3</i>	SIM	LXI S,	STA	INX S	INR M	DCR M	MVI M,	STC	LDES*	DAD SP	LDA	DCX SP	INR A	DCR A	MVI A,	CMC
<i>4</i>	MOV B,B	NOV B,C	MOV B,D	NOV B,E	MOV B,H	MOV B,L	MOV B,M	MOV B,A	MOV C,B	MOV C,C	MOV C,D	MOV C,E	MOV C,H	MOV C,L	MOV C,M	MOV C,A
<i>5</i>	MOV D,B	MOV D,C	MOV D,D	MOV D,E	MOV D,H	MOV D,L	MOV D,M	MOV D,A	MCV E,B	MOV E,C	MOV E,D	MOV E,E	MOV E,H	MOV E,L	MOV E,M	MOV E,A
<i>6</i>	MOV H,B	MOV H,C	MOV H,D	MOV H,E	MOV H,H	MOV H,L	MOV H,M	MOV H,A	MOV L,B	MOV L,C	MOV L,D	MOV L,E	MOV L,H	MOV L,L	MOV L,M	MOV L,A
<i>7</i>	MOV M,B	MOV M,C	MOV M,D	MOV M,E	MOV M,H	MOV M,L	HLT	MOV M,A	MOV A,B	MOV A,C	MOV A,D	MOV A,E	MOV A,H	MOV A,L	MOV A,M	MOV A,A
<i>8</i>	ADD B	ADD C	ADD D	ADD E	ADD H	ADD L	ADD M	ADD A	ADC B	ADC C	ADC D	ADC E	ADC H	ADC L	ADC M	ADC A
<i>9</i>	SUB B	SUB C	SUB D	SUB E	SUB H	SUB L	SUB M	SUB A	SBB B	SBB C	SBB D	SBB E	SBB H	SBB L	SBB M	SBB A
<i>A</i>	ANA B	ANA C	ANA D	ANA E	ANA H	ANA L	ANA M	ANA A	XRA B	XRA C	XRA D	XRA E	XRA H	XRA L	XRA M	XRA A
<i>B</i>	ORA B	ORA C	ORA D	ORA E	ORA H	ORA L	ORA M	ORA A	CMP B	CMP C	CMP D	CMP E	CMP H	CMP L	CMP M	CMP A
<i>C</i>	RNZ	POP B	JNZ	JMP	CNZ	PUSH B	ADI	RST 0	RZ	RET	JZ	RSTV*	CZ	CALL	ACI	RST 1
<i>D</i>	RNC	POP D	JNC	OUT	CNC	PUSH D	SUI	RST 2	RC	SHLX*	JC	IN	CC	JNX*	SBI	RST 3
<i>E</i>	RPO	POP H	JPO	XTHL	CPO	PUSH H	ANI	RST 4	RPE	PCHL	JPE	XCHG	CPE	LHLX*	XRI	RST 5
<i>F</i>	RP	POP PSW	JP	DI	CP	PUSH PS	ORI	RST 6	RM	SPHL	JM	EI	CM	JX*	CPI	RST 7

Alle mit einem * versehenen Befehle fehlen in den Listen der Hersteller !